

D.C. Blocks, a Trap for the Unwary When Using Long Patterns

Application Note

Introduction

It is common in high speed digital applications to use a d.c. block in test setups. For example, it can be useful to isolate a component – such as an optical receiver that requires a bias voltage on the signal path – from either damaging or being damaged by other instruments in the signal path. In addition to attributes such as low insertion loss and good return loss, a key specification of a d.c. block is its frequency response. It is obvious to focus on ensuring that the upper frequency of the range is adequate to pass the desired data signal; while it is less obvious to worry about the low end frequency specification, we will see that it can be equally important.



Pattern	Length (bits)	Lowest Frequency Component for a 10 Gb/s signal
PRBS-7	127	78.7 MHz
PRBS-9	511	19.5 MHz
PRBS-1	12,047	4.9 MHz
PRBS-1	532,767	305 kHz
PRBS-2	38,388,607	1.2 kHz
PRBS-3	12,147,483,647	5 Hz
CJTPAT	2,640	3.8 MHz

Table 1. Lowest frequency components for some common test patterns.

Background

A simple rule of thumb is that the lowest frequency contained in an NRZ spectrum will be around (data rate [in Gb/s]) /(test pattern length). For example, for a 10 Gb/s signal, a PRBS-7 containing 127 bits will have its lowest frequency component around 80 MHz. This and other examples are shown in the table. The frequency we've calculated also corresponds with the line spacing in the spectrum. See Table 1.

As will be obvious by now, a d.c. block that does not have a low enough frequency cutoff at the bottom end might attenuate frequency components of a signal involving a longer pattern, affecting measurement results.

Figure 1 is a reminder of the characteristics of an NRZ data spectrum. Figure 2 shows two example pattern lengths, as well as two d.c. blocks (described in the next section), along with their low end cutoff frequencies.



Figure 1. Reminder of an NRZ spectrum, with nulls at multiples of the bit rate, and $\sin(x)/x$ envelope. The minimum frequency and line spacing are both given by the formula in the text, with examples in Table 1.



Figure 2. The minimum frequency in the longest common test pattern, PRBS-31 (a) is shown alongside one of the commonest short patterns, PRBS-7 (b). The minimum frequencies of two different models of d.c. blocks (c) and (d) are also shown.



Figure 3. Passing 9.95 Gb/s data using a PRBS-31 pattern. (1) shows the signal after passing through the measurement setup but d.c. coupled; (2) has the better of the two d.c. blocks in place, (3) has a 5 MHz lower frequency cutoff and shows significant eye degradation.

A Simple Experiment

We ordered two different model d.c. blocks from the same manufacturer. The two models were:

- (a) 5 kHz to 23 GHz
- (b) 5 MHz to 18 GHz

The maximum frequencies are similar, but there are three orders of magnitude difference in the low end; 5 kHz compared with 5 MHz. As can be seen from Figure 2, for a short pattern such as PRBS-7, both models should be capable of passing the entire low end of the spectrum; for PRBS-31 both are likely to clip the low end, but by not passing appreciable energy below 5 MHz, the second model d.c. block is likely to be altering the signal in a noticeable way. The results of the experiment are shown in Figure 3, with significant closure in the BER Contour observable at low probabilities. A shallow eye diagram would show negligible difference, but a real receiver would be negatively impacted by the block with the higher bottom-end cutoff frequency.

Conclusion

PRBS-31 is a particularly exacting pattern in many ways. As demonstrated above, combining such a long pattern with a d.c. block requires care. Using one that removes appreciable low end energy can affect system performance and measurements. (This was learned through bitter practical experience — much time was wasted trying to track down the source of unexpected results before realizing it wasn't the device under test after all.)

Contact Tektronix:

ASEAN / Australasia (65) 6356 3900 Austria* 00800 2255 4835 Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777 Belgium* 00800 2255 4835 Brazil +55 (11) 3759 7600 Canada 1 (800) 833-9200 Central East Europe, Ukraine and the Baltics +41 52 675 3777 Central Europe & Greece +41 52 675 3777 Denmark +45 80 88 1401 Finland +41 52 675 3777 France* 00800 2255 4835 Germany* 00800 2255 4835 Hong Kong 400-820-5835 India 000-800-650-1835 Italy* 00800 2255 4835 Japan 81 (3) 6714-3010 Luxembourg +41 52 675 3777 Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90 Middle East, Asia and North Africa +41 52 675 3777 The Netherlands* 00800 2255 4835 Norway 800 16098 People's Republic of China 400-820-5835 Poland +41 52 675 3777 Portugal 80 08 12370 Republic of Korea 001-800-8255-2835 Russia & CIS +7 (495) 7484900 South Africa +27 11 206 8360 Spain* 00800 2255 4835 Sweden* 00800 2255 4835 Switzerland* 00800 2255 4835 Taiwan 886 (2) 2722-9622 United Kingdom & Ireland* 00800 2255 4835 USA 1 (800) 833-9200

> * If the European phone number above is not accessible, please call +41 52 675 3777

> > Contact List Updated 25 May 2010

For Further Information

Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tektronix.com

ŧð

Copyright © 2010, Tektronix. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks or registered trademarks of their respective companies.

09/10 EA/WWW

65W-26043-0

