

PQA600C Picture Quality Analyzer Declassification and Security Instructions



077-1141-00

Tektronix

**PQA600C Picture Quality Analyzer
Declassification and Security
Instructions**

Copyright © Tektronix. All rights reserved. Licensed software products are owned by Tektronix or its subsidiaries or suppliers, and are protected by national copyright laws and international treaty provisions.

Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specifications and price change privileges reserved.

TEKTRONIX and TEK are registered trademarks of Tektronix, Inc.

Contacting Tektronix

Tektronix, Inc.
14150 SW Karl Braun Drive
P.O. Box 500
Beaverton, OR 97077
USA

For product information, sales, service, and technical support:

- In North America, call 1-800-833-9200.
- Worldwide, visit www.tektronix.com to find contacts in your area.

Preface

The PQA600C Picture Quality Analyzer is based on the Dell T5810 XL Precision Workstation. Refer to the following *Dell Statement of Volatility — Dell Precision Workstation T5810 XL* for information about data security concerning the PQA600C.



Statement of Volatility – Dell Precision Tower 5810/7810/7910

⚠ CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

The Dell Precision Tower 5810/7810/7910 contains both volatile and non-volatile (NV) components. Volatile components lose their data immediately upon removal of power from the component. Non-volatile components continue to retain their data even after the power has been removed from the component:

List below contains volatile and non-volatile memory ICs used in Dell Precision Tower 5810/7810/7910.

Description	Reference Designator	Volatility Description	User Accessible for external data	Remedial Action (action necessary to lose data)
Embedded Flash memory in embedded controller	UO1	256 K bytes non-volatile memory space. 8.25 K bytes volatile memory space	No	N/A
System BIOS	SPI_1	Non Volatile memory, 16 MByte, System BIOS and Video BIOS for basic boot operation, PSA (on-board diags), PXE diags.	No	N/A
TPM	UF1	Encrypted user keys generated by the TPM device for use by the security software are stored in this NVM.	No	N/A
System Memory – DDR4 DIMM memory	Connectors: DIMM1, DIMM2	Volatile memory in OFF state (see state definitions later in text).	Yes	Power off system.
System EEPROM (only for Precision Tower 7910)	On memory DIMM(s) – one, two, present	Non-volatile EEPROM memory. 32 Mbit device. One Device present on each DIMM. Stores memory-manufacturer data and timing information for correct operation of system memory.	No	N/A
PCH CMOS	US1H	Volatile battery back-backed CMOS memory 256 bytes. Stores CMOS information.	No	Removing the on board coin-cell battery.
Video memory – type	UMA architecture-uses system DDR3.	Volatile memory in off state. UMA uses main system memory size allocated out of main memory.	No	Enter S3-S5 state below.

Description	Reference Designator	Volatility Description	User Accessible for external data	Remedial Action (action necessary to lose data)
Hard drive	User replaceable	Non-volatile magnetic media, various sizes in GB.	Yes	Low-level format.
CD-ROM/RW/ DVD/ DVD+RW/ Diskette Drives	User replaceable	Non-volatile optical/magnetic media.	No	Low-level format/erase.
SAS / SATA Hard Drives and optional storage controller cards	User replaceable	Non-volatile data	No	Low-level format/erase.

All other components on the motherboard will lose data once power is removed from the system. Primary power loss (Unplug the power cord and remove the battery) will destroy all user data on the memory (DDR3, 1333/1600MHz). Secondary power loss (removing the on board coin-cell battery) will destroy system data on the system configuration and time-of-day information.

In addition, to clarify memory volatility and data retention in situations where the system is put in different ACPI power states the following is provided (those ACPI power states are S0, S1, S3, S4 and S5):

- S0 state is the working state where the dynamic RAM is maintained and is read/write by the processor.
- S1 state is a low wake-up latency sleeping state. In this state, no system context is lost (CPU or chip set) and hardware maintains all system contexts.
- S3 is called "suspend to RAM" state or stand-by mode. In this state the dynamic RAM is maintained. Dell systems will be able to go to S3 if the OS and the peripherals used in the system supports S3 state. Windows XP, Windows vista and Windows 7 all support S3 state.
- S4 is called "suspend to disk" state or "hibernate" mode. There is no power. In this state, the dynamic RAM is not maintained. If the system has been commanded to enter S4, the OS will write the system context to a non-volatile storage file and leave appropriate context markers. When the system is coming back to the working state, a restore file from the non-volatile storage can occur. The restore file has to be valid. Dell systems will be able to go to S4 if the OS and the peripherals support S4 state. Windows 7 and Windows 8.1 support S4 state.
- S5 is the "soft" off state. There is no power. The OS does not save any context to wake up the system. No data will remain in any component on the system board, i.e. cache or memory. The system will require a complete boot when awakened. Since S5 is the shut off state, coming out of S5 requires power on which clears all registers.

The Dell Precision Tower 5810/7810/7910 supports all of the above states, except S1.