

Changeover Unit

ECO422D SD/HD Data Sheet



Features & Benefits

- Switches Analog Black and Serial Digital Video, Both Standard and High-definition, and Digital Audio
- Eleven User-configurable Signal Channels
- Amplitude Detection on All Channels
- Electrical Fast Switch Function for Input Channels 4 to 6, with Option ELSW
- Automatic or Manual Operation
- Fault and Operating Mode Front-panel Indicators

Applications

- Provides Complete Fault Tolerance when Used as a Switch Between Primary and Backup SPGs or TSGs

The ECO422D is a highly versatile sync changeover unit designed for use in a serial SD/HD digital television environment. The ECO422D will accommodate component or composite serial digital video signals, AES/EBU digital audio, tri-level sync, and analog black-burst signals. This flexibility makes the ECO422D ideal for both the mixed-format and all-digital television facility.

The ECO422D provides eleven user-configured channels, each channel consisting of primary and backup inputs, and an output.

- Six channels can be set for high-definition serial digital video, standard-definition serial digital video, AES/EBU digital audio, tri-level sync, and PAL or NTSC analog black burst
- Five channels may be set for standard-definition serial digital video, AES/EBU digital audio, tri-level sync, and PAL or NTSC analog black burst

Channel configuration is by internal DIP switch. Signal amplitude fault detection level follows the setting of the channel configuration switches. Detection on individual channels may be disabled, giving the option of disabling changes to the backup unit on failure of signals not critical to the facility operation.

When operated in the switch-on-fault mode, the ECO422D will automatically select the backup sync source should any of the primary inputs fail. However, in the unlikely event both sync sources are faulty, the ECO422D will not alternate between the two sources. If necessary, this function may be overridden with the manual sync source selection. Manual source selection also facilitates periodic testing of the changeover function. Switching is by mechanical relay with all channels switched simultaneously. The Electrical Fast Switch function, available with Opt. ELSW, improves the changeover switching speed between inputs, and replaces the mechanical relay on channels 4-6. Using this type of switch minimizes disturbance when switching between primary and backup inputs. With Opt. ELSW, channels 4-6 can only accept a black-burst or tri-level sync signal.

Front-panel controls are provided for source selection, operating mode, resetting the fault indicators, and for disabling the front-panel controls. LED indicators are also provided. Indication of fault and unit on line is also available through the remote connector.

Characteristics

Inputs and Outputs

Return Loss –

Channels 1-6:

- 30 dB, 0 to 10 MHz.
- 15 dB, 10 to 750 MHz.
- 10 dB, 750 MHz to 1.5 GHz.

Channels 7-11:

- 30 dB, 0 to 10 MHz.
- 15 dB, 10 to 270 MHz.
- 12 dB at 360 MHz (15 dB typical) when selected.

Channels 4-6 (with Opt. ELSW):

- 30 dB, 0 to 10 MHz.

Insertion Loss –

Channels 1-6: 0.2 dB, DC to 10 MHz.

In a frequency range of 10 MHz to 1.5 GHz, the instrument approximates less than 20 meters of Belden 1694A cable.

Channels 7-11:

- 0.2 dB, DC to 10 MHz.
- 0.5 dB, 10 to 200 MHz.
- 1.0 dB, 200 to 360 MHz.

Channels 4-6 (with Opt. ELSW):

- 0.3 dB, DC to 10 MHz

Maximum Switched Voltage –

All channels:

- ±5 V

Channels 4-6 (Opt. ELSW):

- ±1 V (only for the tri-level sync and analog black-burst signals).

Maximum Switched Current – 100 mA.

Crosstalk (Unselected input to output or channel to channel) –

Channels 1-6:

- 60 dB to 10 MHz.
- 30 dB to 1.0 GHz.
- 20 dB to 1.5 GHz.

Channels 7-11:

- 60 dB to 10 MHz.
- 30 dB to 200 MHz.
- 15 dB to 360 MHz.

Channels 4-6 (Opt. ELSW):

- 55 dB to 10 MHz.
- 45 dB to 30 MHz.

Relay Switch Time – Time that it takes for the relays to switch and settle.

Approximately 10 ms.

Channel Switch Time (Channels 4-6, Opt. ELSW only) – Time that it takes for the channel to switch and settle. Approximately 100 ns.

Approximately 100 ns.

Amplitude Detection – The ECO422D will determine a fault condition exists when the input signal is less than 2 dB from the nominal level. The following are the amplitude ranges for the various types of input signals that will result in a fault condition.

Black Burst –


NTSC: 180 to 225 mV.

PAL: 190 to 235 mV.

Tri-level: 150 to 210 mV.

Serial Digital Video – 505 to 630 mV.

AES/EBU Digital Audio – 630 to 790 mV.



Power Source

Mains Ranges –

Voltage: 100 to 240 VAC, ±10%.

Frequency: 48 to 62 Hz.

Power consumption: 25 W maximum.

Environmental

Temperature –

Operating: 0 °C to +40 °C, IEC1010-1 compliance.

Nonoperating: -40 °C to +65 °C.

Altitude –

Operating: To 6562 feet (2000 meters), IEC1010-1 compliance.

Regulatory

EMC – Certified to the EMC Directive 89/336/EEC.

Safety –

Approved to: UL3111-1, CAN/CSA-C22.2 No.1010.1.

Complies with: EN61010-1, IEC1010-1.

Physical Characteristics

Dimension	mm	in.
Height	44	1.734
Width	483	19.0
Depth	561	22.1
Weight	kg	lb.
Net	4.9	10.8
Shipping	8.3	18.3

Ordering Information

ECO422D

Changeover Unit.

Service Options

Opt. G3 – Complete Care 3 Years (includes loaner, scheduled calibration and more)

Opt. G5 – Complete Care 5 Years (includes loaner, scheduled calibration and more)

Opt. R3 – Repair Service 3 Years.

Opt. R5 – Repair Service 5 Years.

Product Options

Opt. ELSW –

Provides Electrical Fast Switch Function for channels 4-6.

Opt. ELSW is installed at the factory, and cannot be added later.



Tektronix is registered to ISO 9001 and ISO 14001 by SRI Quality System Registrar.

Contact Tektronix:

ASEAN / Australasia (65) 6356 3900
Austria 00800 2255 4835*
Balkans, Israel, South Africa and other ISE Countries +41 52 675 3777
Belgium 00800 2255 4835*
Brazil +55 (11) 3759 7627
Canada 1 800 833 9200
Central East Europe and the Baltics +41 52 675 3777
Central Europe & Greece +41 52 675 3777
Denmark +45 80 88 1401
Finland +41 52 675 3777
France 00800 2255 4835*
Germany 00800 2255 4835*
Hong Kong 400 820 5835
India 000 800 650 1835
Italy 00800 2255 4835*
Japan 81 (3) 6714 3010
Luxembourg +41 52 675 3777
Mexico, Central/South America & Caribbean 52 (55) 56 04 50 90
Middle East, Asia, and North Africa +41 52 675 3777
The Netherlands 00800 2255 4835*
Norway 800 16098
People's Republic of China 400 820 5835
Poland +41 52 675 3777
Portugal 80 08 12370
Republic of Korea 001 800 8255 2835
Russia & CIS +7 (495) 7484900
South Africa +41 52 675 3777
Spain 00800 2255 4835*
Sweden 00800 2255 4835*
Switzerland 00800 2255 4835*
Taiwan 886 (2) 2722 9622
United Kingdom & Ireland 00800 2255 4835*
USA 1 800 833 9200

* European toll-free number. If not accessible, call: +41 52 675 3777

Updated 10 February 2011

For Further Information. Tektronix maintains a comprehensive, constantly expanding collection of application notes, technical briefs and other resources to help engineers working on the cutting edge of technology. Please visit www.tektronix.com



Copyright © Tektronix, Inc. All rights reserved. Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX and TEK are registered trademarks of Tektronix, Inc. All other trade names referenced are the service marks, trademarks, or registered trademarks of their respective companies.

02 Oct 2011

20W-07236-5

